

Schauer® Battery Chargers

Schauer is a trademark of the Brookwood Group Inc.



Schauer
3210 Wasson Road
Cincinnati, Ohio 45209

1-800-899-VOLT (8658)

Fax: 1-513-791-7192

www.battery-chargers.com

MODEL JAC0212, JAC0224, JAC0324, JAC0348, JAC0436, JAC0512, JAC0524, JAC0724, JAC1212

Fully Automatic World-Wide Universal Input Electronic Charger



Model JAC0524 Shown With 3 Pin XLR Plug

Model JAC0224 Shown With 3 Pin XLR Plug

Intelligent chargers follow battery impedance to end of charge cycle for all battery types. Fully automatic. Red LED indicates AC power on, yellow LED indicates battery is charging, green LED indicates float mode. Aluminum case.

- World-Wide Universal AC Input 90 – 260 volts, 50/60Hz.
- Charge control: modified constant current charge to a constant finishing voltage then to a float standby.
- Current limiting.
- Fully automatic 3 stage charger can be left on the battery indefinitely.

- For any type lead acid battery, including conventional, maintenance free, deep cycle, gelled-type, valve regulated batteries.
- Finishing voltage: 2.28 volts per cell float; 2.4 volts per cell finishing. May be preset to customers specification for battery type.
- Not intended for use as a DC power supply.
- Full load at 2.1 volts per cell continuous - 100% duty cycle.
- Short circuit proof.
- Reverse polarity protection (except 2 amp model).
- Battery clips, ring terminals strip leads or 3 pin xlr plugs available.

JAC0212 ⁽³⁾	2 AMPS	12 VOLTS	4.6" w x 2.3" h x 1.4" d	1.2 lbs.
JAC0512 ⁽¹⁾	5 AMPS	12 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.
JAC1212 ⁽²⁾	12 AMPS	12 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.
JAC0224 ⁽³⁾	2 AMPS	24 VOLTS	4.6" w x 2.3" h x 1.4" d	1.2 lbs.
JAC0324 ⁽¹⁾⁽³⁾	3 AMPS	24 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.
JAC0524 ⁽¹⁾	5 AMPS	24 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.
JAC0724 ⁽¹⁾	7 AMPS	24 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.
JAC0436 ⁽¹⁾	4 AMPS	36 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.
JAC0348 ⁽¹⁾	3 AMPS	48 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.

(1.) DC cordsets 3' long; with ring terminals or XLR connector. (2.) with stripped leads. (3.) with battery clips.

NOTE: Chargers available for other currents and voltages, contact factory.